

# BIG BUSINESS FEATURES

## SMALL BUSINESS CONVENIENCE



## Colour Wireless LED 4-in-1 Printer

MFC-L9570CDW



PRINT



COPY



SCAN



FAX



WIRELESS

# Colour Wireless LED 4-in-1 Printer

With an impressive 17.6cm colour touchscreen, single pass 2-sided (duplex) scan speeds of 100ipm in colour and a choice of toner cartridges are only some of the highlights of this model.

## MFC-L9570CDW



### Key Features:

- Fast print speeds of up to 31 ppm colour and monochrome
- Single pass 2-sided (duplex) scan speeds of 100 ipm colour and monochrome
- Dual access multi-tasking, print and scan simultaneously
- Maximum paper input of up to 2,380 sheets
- Optional ultra high-yield replacement cartridges, 9,000 page black, cyan, magenta and yellow page toner cartridges
- Gigabit Ethernet and wireless (IEEE 802.11b/g/n) network interfaces
- Integrated NFC card reader
- Intuitive 17.6cm Colour Touchscreen

### Increase productivity levels

- Productivity is increased significantly thanks to the fast print speeds of up to 31 ppm and 2-sided (duplex) scan speeds of 100ipm in colour and monochrome
- Print and Scan simultaneously with dual access multi-tasking
- Outstanding paper handling options with a standard paper capacity of up to 300 sheets, expandable to 2,380 sheets

### Meeting you IT challenges

- Modern businesses demand the highest levels of security. With Secure Function Lock 3.0, Internet Protocol Security (IPsec), 802.1x and Secure Print, you can be confident that your documents are safe
- Create custom IT solutions with open interface platform BSI (Brother Solutions Interface)
- Manage your print fleet with free printer management software BRAdmin Professional 4
- Complete customisable User Interface, enabling up to 64 one-touch buttons

### Flexible and low running costs

- Designed for high volume printing environments, the MFC-L9570CDW includes an inbox super high-yield 6,500 page black, cyan, magenta and yellow toners, and can take an optional ultra high-yield 9,000 page black, cyan, magenta and yellow page toners to lower your running costs even further

General	
Technology	Electrophotographic Laser Printer
Laser Classification	Class 1 laser product (IEC60825-1:2007)
Processor	800MHz – Sub:133Mhz
Local Interface	Hi-Speed USB 2.0 & USBHost
Wired Network Interface	Gigabit Ethernet 10Base-T/100Base-TX/1000Base-T
Wireless Network Interface	IEEE802.11b/g/n
Standard Memory	1GB
Display	17.6cm Colour Touchscreen
Shortcuts	64
Colour Printer	
Print Speed Standard (A4)	Up to 31 ppm (pages per minute) colour & monochrome
Print Speed 2-sided (duplex) (A4)	Up to 14 sides per minute (7 sheets per minute) colour & monochrome
Resolution	2,400dpi (2,400 x 600dpi), 600 x 600dpi
Quiet Mode	A mode to reduce the printing noise by reducing the print speed to 15 ppm
FPOT (First Print Out Time)	Less than 15 seconds colour & monochrome from ready mode
Warm Up Time	Less than 31 seconds from sleep mode
Print Languages	PCL6, BR-Script3 (PostScript®3™ Language Emulation), PDF 1.7, XPS1.0
Embedded Fonts (PCL)	66 scalable fonts, 12 bitmap fonts, 16 barcodes
Embedded Fonts (Postscript)	66 scalable fonts
Embedded Barcodes (PCL)	Code39, Interleaved 2 of 5, FIM (US-PostNet), Post Net (US-PostNet), EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN (EAN), ISBN(UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C), Code93, GS1Databar, MSI

Printer Functions	
N-up Printing	Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)
Poster Printing	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages
Watermark Printing	Watermark your documents with predefined text or with your own user-defined messages
ID Printing	Add identification to your printed documents (date & time, short custom message or PC username)
Automatic 2-sided (duplex) Print	Print on to both sides of the paper automatically
Manual 2-sided (duplex) Print	Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex) print)
Booklet Printing	Print documents in A5 booklet format using automatic or manual 2-sided (duplex) print
Print Profiles	Store your favourite driver settings as profiles to easily recall them
Printer Drivers	
Windows®	Windows® 11, Windows® 10 (32&64bit), Windows® 8/8.1 (32&64bit), Windows® 7 (32&64bit), Windows® Server 2019, Windows® Server 2016, Windows® Server 2012/R2 (64bit), Windows® Server 2008 (32&64bit), Windows® Server 2008 R2
Macintosh®	Mac OS X 10.10.5 - 10.15, macOS 11f
Linux®	CUPS, LPD/LPRng (32 & 64 bit editions)
PostScript Universal Printer Driver	Driver for Windows® that enables you to print to any network or locally-connected Brother laser printer that supports PostScript
PCL Driver	Generic PCL XL driver

<b>NFC</b>	
Integrated NFC	Supports NFC cards for secure authentication or shortcuts and NFC supported mobile devices for direct printing and scanning
External NFC Card Reader Support	Support for external NFC readers via the front USB port
<b>Standard Paper Handling</b>	
Paper Input <sup>2</sup>	Lower Tray – 250 sheets Multi Purpose Tray – 50 sheets Automatic Document Feeder – 80 sheet
Paper Output <sup>2</sup>	Face Down - 150 sheets Face Up (Straight Paper Path) - 1 sheet
<b>Optional Paper Handling</b>	
Paper Input <sup>2</sup>	250 Sheets (LT-330CL) 500 Sheets (LT-340CL) Maximum of 3 optional tray (LT-330) or maximum of 2 optional trays (LT-340CL and/or LT-330CL) 4 x 520 sheet tower tray (TT-4000 & TC-4000)
<b>USB Host</b>	
Direct Print	Print directly from a USB flash memory drive. The supported file formats include: PDF version 1.7, JPEG, Exif+JPEG, PRN (created by own printer driver), TIFF (scanned by Brother model), XPS version 1.0
Direct Scan	Scan directly to a USB flash memory drive. The supported file formats include: PDF, PDF/A, Secure PDF, Signed PDF, JPEG, XPS, TIFF
USB Input Port	Rear USB port for use with an external NFC card reader
<b>Paper Input/Output Sensors</b>	
Input	Onscreen & optional email alerts notifying you when any of the paper input trays are nearly empty or empty
<b>Media Specification</b>	
Media Types & Weights	<b>Standard Tray</b> – plain, recycled, coloured and letterhead (between 60 - 105g/m <sup>2</sup> ) <b>Multi Purpose Tray</b> - plain, recycled, bond, coloured, letterhead and glossy <sup>a</sup> paper (between 60-163g/m <sup>2</sup> ) <b>2-sided (duplex) Print</b> - plain, recycled, coloured, letterhead and glossy <sup>a</sup> paper (between 60 - 105g/m <sup>2</sup> ) <b>Automatic Document Feeder</b> - Plain & recycled paper (between 64 - 90g/m <sup>2</sup> )
Envelope & Label Printing	Yes, from the Multi Purpose Tray: support for 10 envelopes up to 10mm total thickness
Media Sizes	<b>Standard Tray</b> - A4, Letter, A5, A5(Long Edge), A6, Executive, Legal, Folio, Mexico Legal <b>Multi Purpose Tray</b> - Width: 76.2mm to 215.9mm Length: 127mm to 355.6mm <b>Automatic Document Feeder</b> - Width: 105mm to 215.9mm Length: 147.3mm to 355.6mm <b>2-sided (duplex) Print</b> – A4
<b>Colour Scanner</b>	
Scanner Type	Dual CIS (Contact Image Sensor)
Automatic 2-sided (duplex) Scanning	Yes
Colour & monochrome Scanning	Yes
Scan Speed	50 ipm (images per minute) colour & monochrome
2-sided Scan Speed	100 ipm (images per minute) colour & monochrome
Scan Resolution from ADF	Up to 1,200 x 600dpi
Scan Resolution from Scanner Glass	Up to 1,200 x 2,400dpi
Interpolated Scan Resolution <sup>7</sup>	Up to 19,200 x 19,200dpi
Colour Depth	16, 777, 216 colour variations (48 bit)
Grey Scale	256 shades of grey (8 bit)
Standard Functions <sup>7</sup>	Scan to USB, E-mail, OCR, Image & File
Network Scanning	Scan to network folder (Windows <sup>®</sup> only), FTP, SFTP, Email Server, SharePoint (Local infrastructure only) & Easy Scan to Email <sup>®</sup>
Cloud Scanning <sup>®</sup>	Scan direct to Box, Dropbox, Evernote <sup>™</sup> , Google Drive <sup>™</sup> , OneDrive, OneNote
Scan Features	Remove Background, Skip Blank Page, ID Scan, 1 to 2 Scan, Auto Deskew from ADF, Split PDF
Scan to Microsoft Office	Scan to Microsoft <sup>®</sup> Word, Microsoft <sup>®</sup> Excel & Microsoft <sup>®</sup> PowerPoint
Scan to Searchable PDF	Scan documents to searchable PDF files
Scan to SharePoint (Local infrastructure only)	Scan documents directly into SharePoint
Windows <sup>®</sup> Web Services Scanning	Scan direct into Windows <sup>®</sup> (from Windows <sup>®</sup> 7 & onwards) without needing to install a scanner driver

<b>Scanner Driver</b>	
Windows <sup>®</sup>	TWAIN, WIA & ISIS Windows <sup>®</sup> 11, Windows <sup>®</sup> 10 (32 & 64 bit editions) Windows <sup>®</sup> 8 (32 & 64 bit editions), Windows <sup>®</sup> 7 (32 & 64 bit editions),
Macintosh <sup>®</sup>	TWAIN & ICA Mac OS v10.10.5, v10.11.x, v10.12
Linux <sup>®</sup>	SANE (32 & 64 bit editions)
<b>Address Book</b>	
Speed Dials	300 locations for E-mail addresses and Fax numbers
Group Dial	A combination of up to 20 groups can be stored for broadcasting
LDAP	The ability to connect to an external LDAP enabled address book, like Microsoft <sup>®</sup> Exchange
<b>Colour Copier</b>	
Speed – (A4)	Up to 31cpm (copies per minute) colour & monochrome
FCOT (First Copy Out Time)	Less than 17 seconds colour & less than 16 seconds monochrome from ready mode
Resolution	Up to 1,200 x 600dpi
Multi-Copying / Stack / Sort	Makes up to 99 copies of each page / Stacks or Sorts
Enlargement / Reduction Ratio	Reduce or Increase document sizes from 25% to 400% in 1% increments
N in 1 Copying	Allows the user to compress 2 or 4 pages on to a single A4 sheet
2in1 ID Copying	Allows the user to copy both sides of an ID card to a single A4 sheet
Grey Scale	256 shades of grey are available for copying
Receipt Copying	Produces clearer copies of receipts
<b>Mobile / Web Based Printing &amp; Scanning</b>	
Brother iPrint&Scan (Android)	Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an Android device
Brother iPrint&Scan (iPad / iPhone / iPod)	Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an iPad / iPhone / iPod Touch
Brother iPrint&Scan (Windows <sup>®</sup> Phone)	Print from and scan to a smart phone running the Windows <sup>®</sup> Phone Operating System
Brother Print&Scan (Windows <sup>®</sup> 8, 10 & RT)	Print from and scan to a Windows <sup>®</sup> 8, 10 or Windows RT Tablet
AirPrint	Print most common file types from any AirPrint enabled application
Mopria	Print most common file types from Mopria supported Android devices
Brother Print Service Plugin	Print from Android devices without a dedicated App
Box <sup>®</sup>	Print from and scan to Box without using a PC
Dropbox <sup>®</sup>	Print from and scan to Dropbox without using a PC
Evernote <sup>™</sup>	Print from and scan to Evernote <sup>™</sup> without using a PC
Google Drive <sup>™</sup>	Print from and scan to Google Drive <sup>™</sup> without using a PC
OneDrive <sup>®</sup>	Print from and scan to Microsoft <sup>®</sup> OneDrive without using a PC
OneNote <sup>®</sup>	Scan to Microsoft <sup>®</sup> OneNote without using a PC
Creative Centre <sup>®</sup>	Download and print Brother Creative Center content
<b>Fax</b>	
Fax Modem	33,600bps (SuperG3)
Automatic 2-sided (duplex) Faxing	Yes
Internet Fax (iFax) <sup>®</sup>	Fax documents anywhere in the world over the Internet without the use of a telephone line
Fax to Server	Sends faxes to a server
PC Fax Send	Send faxes directly from your PC
PC Fax Receive	Receive faxes directly to your PC
Automatic Redial	Automatic redialling if the recipient fax is busy
Telephone Index	An electronic, alphabetical listing of stored speed dials and group numbers
ChainDialling	Allows the user to store parts for long dialling sequences in different speed dial locations
Distinctive Ring Detection	An external service that allows two telephone numbers shared on a single fixed line and use different ring tones
Speaker / Ring volume	3 levels on/off
Fax / TelSwitch	Automatic recognition of fax and telephone reception
Super Fine	Enables quality transmission of very small print and line drawings

<b>Contrast</b>	Auto / light / dark
<b>Enhanced Remote Activate</b>	Transfer a fax call, answered on an extension phone, to the fax machine
<b>Delayed Timer</b>	Up to 50
<b>Quick-Scan</b>	Approximately 2.5 seconds per page A4 standard resolution
<b>Memory Transmission</b>	Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)
<b>Out of Paper Reception</b>	up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)
<b>Dual Access</b>	Allows the operator to perform 2 different tasks on the machine at the same time
<b>Broadcasting</b>	Send the same fax message to up to 350 separate locations (manual 50 locations)
<b>Batch Transmission</b>	Stores documents for the same location in the machines memory for transmission in a single call
<b>Auto Reduction</b>	When receiving a single page document longer than A4 (297mm) the fax machine will automatically reduce the message to fit onto a single A4 sheet
<b>ECM (Error Correction Mode)</b>	The MFC will detect line errors during fax transmission and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work)
<b>Fax Forwarding</b>	Sends a fax received in memory to another preprogrammed fax number or e-mail address
<b>Remote Access</b>	Allows users to remotely access their machine
<b>Fax Retrieval</b>	Allows remote access to faxes stored in the machine
<b>Remote Maintenance</b>	Allows users to maintain their MFC remotely
<b>Remote Set-up<sup>3</sup></b>	Allows users to set-up the MFC from their PC
<b>Grey Scale</b>	256 shades (8 bit) of grey are available for faxing
<b>Fax Preview</b>	Preview received faxes on the screen
<b>Fax Stamp</b>	Add the date and time to all received faxes
<b>Cover Page</b>	Create custom cover pages for outgoing faxes

## Network & Security

<b>Wired Network</b>	Built in Ethernet 10Base-T/100Base-TX/1000Base-T
<b>Wireless Network</b>	IEEE 802.11b/g/n (Infrastructure Mode)
<b>Wi-Fi Direct™</b>	Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)
<b>Wireless Setup Support</b>	Wi-Fi Protected Setup (WPS)
<b>Wireless Applications</b>	Vertical Pairing
<b>Network Protocols</b>	TCP/IP (IPv4 and IPv6)
<b>IPv4</b>	ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, POP3, SMTP Client, IPP/PPS, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print/Scan), SNTIP Client, LDAP, IMAP4
<b>IPv6</b>	NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/PPS, POP3, SMTP Client, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, SNTIP Client, LDAP, Web Services (Print/Scan), IMAP4
<b>Wired Network Security</b>	APOP, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP3, IMAP4), SNMP v3 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos, IPsec
<b>Wireless Network Security</b>	WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK(TKIP/AES) APOP, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP3, IMAP4), SNMP v3, Kerberos, IPsec, 802.1x (LEAP, EAP-FAST, PEAP, EAP-TLS, EAPTTLS)
<b>Print Log To Network</b>	Records printing activities from each individual user, including network username, name of document printed and number of pages, to a file on a network
<b>E-mail Notifications</b>	Automatically have the device send an E-mail to a nominated E-mail address when it requires attention
<b>E-mail Reports</b>	Receive usage reports on a regular basis via E-mail
<b>IPv4 Filter</b>	Restrict which network users either can or cannot access the device over the network
<b>Secure Function Lock 3.0</b>	Restrict access to individual or groups of users over a network. Can be used with PC User Login Names for up to 200 users
<b>Setting Lock</b>	Restrict access to the control panel by securing it with a 4 digit PIN
<b>Secure Print<sup>3</sup></b>	Protect print jobs with a 4 digit PIN that has to be entered at the control panel of the printer before printing
<b>Active Directory Authentication</b>	Retrieve stored print jobs & control access to the devices functionality by using credentials from Active Directory
<b>LDAP Authentication</b>	Retrieve stored print jobs & control access to the devices functionality using credentials from an LDAP supported database

## Fleet Management Tools

<b>Unattended Installer<sup>1</sup></b>	Ability to centrally deploy and customise our drivers and software
<b>MSI Installer<sup>4</sup></b>	Modular installers that can be distributed through Active Directory <sup>5</sup>
<b>Embedded Web Server</b>	Web based print management software embedded onto the device
<b>BRAdmin Professional<sup>4&amp;5</sup></b>	Fleet management software
<b>Driver Deployment Wizard<sup>4</sup></b>	Easily create print drivers for hassle free deployment over your network

## Developers

<b>Brother Solution Interface (BSI)</b>	Create powerful cloud and on premise solutions directly integrating the advanced print, scan and security capabilities of Brother scanners, printers and all in ones. For more information visit: <a href="http://corpsolutions.brother.com.au">http://corpsolutions.brother.com.au</a>
<b>Supplies &amp; Accessories</b>	
<b>Super High-yield Inbox Toners</b>	Black Toner – 6,500 pages <sup>1</sup> Cyan, Magenta & Yellow Toners – 6,500 pages <sup>1</sup>
<b>Ultra High-yield Toners</b>	Black Toner (TN-449BK) 9,000 pages <sup>1</sup> Cyan Toner (TN-449C) 9,000 pages <sup>1</sup> Magenta Toner (TN-449M) 9,000 pages <sup>1</sup> Yellow Toner (TN-449Y) 9,000 pages <sup>1</sup>
<b>Other Supplies</b>	Drum (DR-441CL) Approx. 30,000 pages (1page/job) Approx. 50,000 pages (3page/job) Belt (BU-330CL) Approx. 50,000 pages (1page/job) Approx. 130,000 pages (3page/job) Waste Toner Box (WT-320CL) Approx 50,000 pages
<b>LT-330CL</b>	Optional 250 sheet Lower Tray (Maximum of 3)
<b>LT-340CL</b>	Optional 500 sheet Lower Tray (Maximum of 2)
<b>TT-4000</b>	Tower Tray 4 x 520 sheet (TC-4000 also needed)
<b>TC-4000</b>	Tower Tray Connector
<b>CH-1000</b>	Card Reader Holder
<b>Carton Contents</b>	Toner Cartridges, Drum, Belt, Waste Toner Box, Power Supply Cord, Driver Software For Windows®, Quick Set-Up Guide, PC Interface Cable NOT Included, Telephone line cord

## Environment

<b>Power Consumption</b>	Printing - 580W, Ready - 70W, Sleep - 10W, Deep sleep - 1.7W, Power down - 0.03W
<b>Sound Pressure Level</b>	Printing - 49dbA, Quiet mode printing - 44dbA, Ready - inaudible
<b>Sound Power Level</b>	Printing - 6.56BA, Quiet mode printing - 6.0BA, Ready - inaudible
<b>Power Saving</b>	This enables the printer to consume less energy when not in use
<b>Toner Save Mode</b>	This reduces the toner usage and helps to reduce the total cost of printer ownership
<b>Duty Cycles</b>	
<b>Recommended Monthly</b>	Up to 6,000 pages monthly print volume
<b>Maximum Monthly<sup>8</sup></b>	Up to 80,000 pages monthly print volume
<b>Dimensions &amp; Weight</b>	
<b>With Carton (WxDxH)</b>	675 x 652 x 726mm (36.1kg)
<b>Without Carton (WxDxH)</b>	495 x 526 x 549mm (29.7kg)

The frequency of replacement consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, page per job, and the type of media. For example glossy coated paper will result in a shortened life of such supplies.

- 1 Approx declared yield value in accordance with ISO/IEC19798
- 2 Calculated with 80g/m<sup>2</sup> paper
- 3 Windows® & Mac only
- 4 Windows® only
- 5 Optional download
- 6 Must be webconnected
- 7 Requires Brother software
- 8 Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements
- 9 Only a single sheet supported in the Multi Purpose Tray

All specifications correct at time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.



### Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth. [www.brotherearth.com](http://www.brotherearth.com)



**brother**  
at your side